

FW9707-FNR

2MP IR Speed Dome

FW9707-FNR is a high-quality IR PTZ IP camera which is equipped with 2.48MP Progressive Scan CMOS image Sensor. With the highest sensitivity sensor, it is especially superior in low light condition. As it supports simultaneous H.265, H.264 and MJPEG Video Compression, less network bandwidth and storage space required. It also delivers high quality video image at 30fps@2M in progressive mode.

Key Features

- Backdoor Issue free
- Panasonic 1/3" 2.48MP PS CMOS sensor
- Optical 30x zoom, Digital 32x zoom
- 4 steps zoom proportional IR LED working up to 300m
- Quadruple Stream H.265, H.264, M-JPEG, JPEG
- Max. 30fps @ 2MP
- Built-in FAN/HEATER
- OnVIF Profile S standard
- Al function (optional)
- Auto tracking (optional)
- WIPER (optional)





WIPER (Option)

Tech Notes

Intelligent Varifocal IR LED control: IR PTZ

The IR beam automatically adapts becoming wider or narrower as the camera zooms in or out.


Text OSD

User can set 9 set of text strings to display direction of the camera or location of the camera. Each string can be extended up to 24 alphanumeric characters. When PTZ moves to the pre-set PAN angle up to 8, it automatically displays the text string set on the PAN angle like "to Las Vegas" or "-> Los Angeles"



FW9707-FNR

Technical Specifications



Camera	
Image Sensor	1/1.3" Panasonic 2.48MP CMOS
Lens	Optical 30x (Digital 32x)
	f-4.3~129.0mm (F1.6~F4.7)
	FOV(H): 65.1~2.34 degrees
Day & Night	True Day & Night (ICR)
Min. Illumination	Color 1/30s: 0.05 lux, B&W 1/30s: 0.005 lux
	Color DSS on : 0.002 lux, B&W : 0.0001 lux
IR illumination	300m, 13ea. 850nm IR hi-power LED
Pan Tilt Zoom	Pan: 360 ° Endless
	Tilt : 0 °~ 90 °
	Optical Zoom 30x, Digital Zoom 32x
	255 Presets, 8 Group, 8 Tour, 8 Swing,
	Auto flip, Auto parking, Power-up action.
	Text display by 9 Pan angles.
Video Stream	
	Ambarella 32bit Embedded Linux
	256Mbyte SDRAM, 128Mbyte NAND Flash
System	
	(optional: 64bit RISC-V Quad Core up to
	594MHz, NOR Flash 512 Mb / LPDDR3 4Gb)
Compression	H.265, H.264, M-JPEG, JPEG
Video Stream	Quadruple Streaming
Resolution	1920x1080, 1280x1024, 1280x720, 704x480,
	640x480, 320x240
Max. Frame rate	Max. 30fps/25fps @ 2MP
Bit Rate Control	VBR/AVBR/CBR/ACBR, GOP
Video Setting	
Exposure Control Mode	Auto/ Manual/ Shutter Priority/ Iris Priority
Focus Control	Auto Focus/ Manual Focus/ Manual Trigger/
	Zoom Trigger/ Interval Trigger
Electronic Shutter	1/6~1/30,000s
Exposure Compensation	-12dB ~ +12dB
Slow Shutter	Off / On
AGC	0 ~ 10
Back Light Mode	BLC, HLC, WDR, ACE
Day-Night Mode	Auto/ Day/ Night
White Balance	Auto/ Indoor/ Outdoor/ OnePush/ Manual
Digital Noise Reduction	Off/ Auto/ Low/ Mid/ High
Image Adjustment	HLC, Stabilizer, Gamma
Text OSD	9 lines, settable size, color, position, etc.
Smart Video	ROI (Region of Interest) 8 areas

	_
Privacy Masking	8 Areas
Analytics	
Motion Detection	4 areas
Object Detection (optional)	Deep learning based Al
	Person, Bicycle, Motorcycle, Car, Truck, Bus,
	Face detection
Video Analytic (optional)	Intrusion Detection, Line Crossing, Object
	Counting, Object Tracking, Tampering, Auto
	Tracking
Network	
Security	IP Filtering, HTTPS, Encrypted & Basic
	Authentication, Management White List
	HTTP, RTP/RTSP (Uni/Multicast), TCP/IP
Supported Protocols	(v4/v6), UDP, FTP, Telnet, HTTPS, RARP,
	SNMP (option), DHCP, NTP, SMTP client, uPnP,
	ZeroConf
DDNS	www.ipcctvdns.com
Interface	RJ45 Ethernet 10/100Mbps
Cybersecurity	
Asymmetric Encryption Algorithm	RSA 2048 bits
Digital Signature Algorithm	RSA 2048 bits
Symmetric Encryption Algorithm	AES-128, AES-256
Cryptographic Hash Functions	SHA-256, MD5
Token Authentication Code	SHA-256, MD5
Key Exchange Protocols	RSA Key Exchange
Certificate	X.509
System Integration	
Application Programing Interface	SDK, ONVIF Profile S
Event Condition	Motion detection, audio detection, external digital
	input, external input data, SD card error
	Pre-alarm & Post-alarm buffer
Event Action	Image upload: FTP (periodic, buffer)
	Notification: email, HTTP, TCP, UDP
	External digital output
Peripheral & Auxiliary I/O	
Onboard Recording	MicroSD card slot
	Line in, line out
Audio	Audio compression: G.711-ulaw, Sampling rate
Audio	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono
	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way
External alarm	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC)
External alarm Serial interface	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485
External alarm Serial interface Video out	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC)
External alarm Serial interface Video out Software	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog)
External alarm Serial interface Video out Software Web Browser	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge
External alarm Serial interface Video out Software	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog)
External alarm Serial interface Video out Software Web Browser	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge
External alarm Serial interface Video out Software Web Browser Mobile Viewer	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android
External alarm Serial interface Video out Software Web Browser Mobile Viewer CMS	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android Smart Multi Viewer and Player
External alarm Serial interface Video out Software Web Browser Mobile Viewer CMS NVR	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android Smart Multi Viewer and Player SmartNVR (up to 9 channels free license)
External alarm Serial interface Video out Software Web Browser Mobile Viewer CMS NVR Device manager	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android Smart Multi Viewer and Player SmartNVR (up to 9 channels free license)
External alarm Serial interface Video out Software Web Browser Mobile Viewer CMS NVR Device manager General Case/ Color	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android Smart Multi Viewer and Player SmartNVR (up to 9 channels free license) IP Installer
External alarm Serial interface Video out Software Web Browser Mobile Viewer CMS NVR Device manager General	Audio compression: G.711-ulaw, Sampling rate 8KHz, 16bit, Mono Audio streaming: 2-way 4 digital input, 2 digital output (NO/NC) 1 RS485 CVBS (SD analog) IE, Chrome, Edge iOS, Android Smart Multi Viewer and Player SmartNVR (up to 9 channels free license) IP Installer Metal

PoE: 60W (optional)

Power Consumption	Max. 42W
Operating Environment	-35°C ~ +60°C, 10% ~ 90% RH
Dimension	228φ x 356(H)mm
Weight	About 6,000g without Bracket & Adapter
Protection	IP66, IK10
Certifications	KC, CE, FCC, RoHS
Included Accessories	AC adapter 24V/3A, waterproof RJ45 connector
	cap, hexagon key L-wrench

Note:

^{*} Specifications are subject to change without notice for product improvement.

^{*} All capabilities may not perform perfectly all the time because their performance can be affected by the environment and the content they are trained on.

^{*} IR illumination's range is dependent on the scene.