

BX-15 Outdoor Bell Box

Protecting Large Premises with High-Powered Sirens and Strobes



- Extensive RF range
- Superb reliability
- Fast signal transmission
- Long battery life
- Unique alarm sounds for fire and burglary

BX-15 is a battery-operated outdoor bell box that deters potential intruders and alerts you to emergencies with loud 102dB siren sound and high-powered strobe light. Enclosed in an IP44 waterproof housing, this series of wireless bell box generates different alarm sounds for fire and burglary to instantly inform users of the type of danger at hand.

BX-15-F1 adopts Climax's latest RF technology to deliver record-breaking communication range and superb reliability, making the bell box a top choice to protect large residential or commercial premises. Featuring fast RF transmission, F1 model sends signals to control panels speedily without increasing power consumption. This advantage of efficient transmission allows its battery life to last longer and reduces maintenance costs.

In addition to producing audible and visible warnings in the case of emergency, BX-15 series emits squawk notifications of arming/disarming/low battery status and transmits supervisory and low battery signals to the control panel to ensure normal operation. The anti-tamper design further prevents unauthorized removal and vandalism.

Features

- Battery-operated
- Extensive RF range (F1 model only)
- Superb reliability
- Long battery life
- Fast signal transmission
- Siren output level is 102dB at 1 meter
- Attractive design and high-powered strobe light (choice of red or blue lens)
- Unique alarm sounds for fire and burglary
- Squawk notifications of arming, disarming, and low battery status
- Programmable siren duration of 3/5/10 minutes
- Dip switch allows manual control of strobe light and alarm duration
- Transmits low battery and supervisory signals
- Antenna design for optimal wireless performance
- Tamper protection prevents unauthorized removal and vandalism
- IP44 waterproof and UV resistant housing
- Compliant with CE requirements

BX-15 Outdoor Bell Box

Specifications

BX-15-F1

Frequency	433 MHz / 868 MHz
Power Source	Alkaline D battery x 4
Battery Life	3 years*
Siren Output	102dB at 1 meter
Lens Color	Blue / Red
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	257 mm x 220 mm x 69 mm

*Note: Actual battery life may vary with product settings, operating environment, and usage.

BX-15

Frequency	433 MHz / 868 MHz
Power Source	Alkaline D battery x 4
Battery Life	433 MHz: 3.6 years* 868 MHz: 2.5 years*
Siren Output	102dB at 1 meter
Lens Color	Blue / Red
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	257 mm x 220 mm x 69 mm

*Note: Actual battery life may vary with product settings, operating environment, and usage.

Ordering Information

BX-15-F1	Outdoor Bell Box, compatible with AC-powered Climax's F1 control panels
BX-15	Outdoor Bell Box